LED Technologies
Creative LED & Effect Technology for the Trade Professional

LEDTech RGB Square Wall Mounted Touch Controller



Product Code:	100.293
Product Type:	Controller / Receiver
Guarantee Period:	1 Year
Control Distance:	20m
Colour Control:	RGB
Size:	86 x 86 x 47mm

Features & Benefits:

- Touch sensitive
- Compact ergonomic design
- Wall mounted
- 16 pre-set programmes

Set Up

Connect the LED lighting units to the terminal block in the rear of the touch controller. Take care to connect the +, Red, Green & Blue connections to the appropriate terminals. Connect a suitable 12v or 24v power supply to the Power Input terminals depending on the voltage of the LED lighting you are controlling.

Powering On

After applying power to the wall switch you will notice that the central button will illuminate amber to indicate standby. Touch the central On / Off button to power on the LED lighting (the central button non longer illuminates). Touching the button again will switch off the LED lighting and the button will glow amber again.

Adjusting the Brightness

Control over the brightness is achieved by touching the brightness button (top right) this button together with the + & - buttons will then glow green to indicate that they are active. By tapping the + or - buttons the brightness of the LED can be adjusted in steps.

Note: If the brightness is adjusted and then the unit is then switched off, when it is switched back on, the level of brightness selected will be resumed

Colour Selection Modes

There are two colour modes, manual colour selection using the rainbow disc and colour program mode

Manual Colour Selection

Adjusting the colour manually is achieved running your finger around the Colour Disc on the unit

Colour Program Mode

There are 16 different selectable colour programs built into the unit. Some programs are adjustable to vary the speed at which the program runs and other programs are dimmable. Press the Program Select button (Top Left) to select a program. The programs are selected by repeatedly pressing the Program Select button and are selected in the order listed below.

Note: When in program mode pressing the + & - buttons will control the speed at which the program runs. If the unit is switched off during a program or light level, when switched on again, the program and light level will be remembered.

We reserve the right to change specifications without notice. E&OE

If you require Technical support or for general enquiries, please do not hesitate to contact one of our LED Technical experts on the contact information provided.

Telephone: 01260 540014
Opening times: Mon-Thur: 8:30am - 5:00pm
Fri: 8:30am - 4:30pm
www.ledtechnologies.co.uk